

TM-1 STUDIO TIMER

The Radio Systems Studio Timer is designed as a versatile, easy to operate broadcast accessory with the capability of timing events out to 9:59:59. The timer will readily and simultaneously interface with all types of tape machines, turntables and other studio equipment for automatic operation.

Operation and Remote Connections

Three front panel pushbuttons control timer functions. "Reset" returns the display to 0:00:00 when in either the run or stop mode. "Start" initiates or continues the count and "Stop" holds the display reading constant.

All three functions can be remotely controlled through rear panel connections. "Start" and "stop" functions are activated through a return to ground connection.

Multiple machine interface connections are provided for the reset function so that the unit can be made to automatically count and display last-event timing. Terminals are provided for up to 3 pull-to-ground and 3 push-from-ground to +15V to +24V remote connections. All 6 terminals can be utilized simultaneously. Each terminal is isolated and capacitively coupled so that machines will not see each other and the timer will reset (and, if in the run mode—begin to count again) from either a pulsed or holding connection.

Limited Warranty

Radio Systems warrants for one year from date of purchase, parts and labor on any unit returned to us for repair. Please ship the unit prepaid with a note detailing the malfunction and reason for return. Repair and return of the unit will be made promptly. Within the warranty period, there is no charge for this service on units which show no sign of misuse or unauthorized alterations.

RADIO SYSTEMS INC.

601 Heron Drive P.O. Box 458 Bridgeport, NJ 08014-0458

609/467-8000 FAX 609/467-3044

